

200A Mini AC Clamp Meter + NCV Detector

Built-in Non-contact Voltage Detector

Take high resolution low current readings with the added safety of an integrated non-contact voltage detector

Features:

- Clamp meter with built-in AC Voltage detector and flashlight
- 0.7" (18mm) jaw opening
- 2000 count backlit LCD display
- Non-contact AC Voltage detector (100 to 600VAC) via clamp tip
- Built-in white LED flashlight
- Continuity and Diode Test
- Max Hold
- Auto power off
- Over range and low battery indicators
- Complete with test leads, pouch case, and two AAA batteries



Non-contact voltage detection via clamp tip



Built-in flashlight for measurements in poorly lit areas

Specifications	Range	Resolution	Accuracy (%rdg+digits)
AC Current	200A	100mA	±(3.0% + 8d)
AC Voltage	600V	0.1mV	±(1.5% + 2d)
DC Voltage	600V	0.1mV	±(0.5% + 1d)
Resistance	20MΩ	0.1Ω	±(3.0% + 5d)
Dimensions	7 x 2.5 x 1.3" (178 x 65 x 32mm)		
Weight	6oz (170g)		

Ordering Information:

MA150.....200A Mini AC Clamp Meter + NCV Detector

