

RUMENTS Product DATASHEET

Mini Pocket MultiMeter

Autoranging with 8 functions including Frequency, Capacitance, and Duty cycle

Features:

- Large high contrast 4000 count LCD display
- Auto Power off to conserve battery life
- Autoranging with Relative and Data Hold
- Diode Test and Continuity Beeper
- Built-in storage compartment for integrated test leads
- Protective rubber holster provides extra protection on the meter
- Over-range and low battery indication
- Complete with test leads, protective holster, one CR 2032 button battery and carrying case

Applications:

- · Home wiring projects
- · Testing electrical systems on cars and boats
- Hobby projects



Specifications	Range	Max. Resolution	Basic Accuracy (%rdg+digits)
DC Voltage:	500V	1mV	±(1.3% + 3d)
AC Voltage:	500V	1mV	±(2.3% + 5d)
Resistance:	400 to 40MΩ	0.1Ω	±(2.0% + 5d)
Capacitance:	100µF	0.001nF	±(3.0% + 15d)
Frequency:	5Hz to 10MHz	0.001Hz	±(2% +5d)
Duty Cycle:	0.1% to 99.9%	0.1%	±1.2%
Diode Test:	Test Current at 0.6mA		
Continuity Test:	Audible beep $<60\Omega$		
Dimensions:	4.25 x 2.2 x 0.5" (108 x 56 x 11.5mm)		
Weight:	1.7oz (50g)		



Ordering Information:

DM100.....Mini Pocket MultiMeter



EXTECH INSTRUMENTS CORPORATION 285 Bear Hill Road, Waltham, MA 02451-1064 Phone: 781-890-7440 • FAX 781-890-7864 ISO 9001:2000 CERTIFIED

Make mine an Extech![™] www.extech.com

09/24/04 - R1